



Beco Works, Cricket Lane, Off Kent House Lane, Beckenham, Kent, BR3 1LA  
Tel: 020 8778 4271 Fax: 020 8659 3576  
E-mail sales@pts-jung.co.uk WWW: www.pts-jung.co.uk

## LEVEL ALARM SYSTEM (PTS.SA1) MAINS-POWERED WITH BATTERY BACK-UP



### FEATURES:

- Electronic alarm;
- Power 1~ 50/ 60Hz 230V + / - 10%
- N°1 inlet in low tension for alarm control from free contact;
- N°1 inlet in low tension for alarm control from free contact N.C.
- Green led "Power on"
- Red led "Alarm"
- Red led "Siren Excluded"
- N° 1 but ton "TEST" for temporary sounder activation
- N° 1 but ton "RESET" for manual restore of alarm condition
- N° 1 but ton "SIREN ACTIVATION" for the activation of the sounder
- N° 1 but ton "SIREN EXCLUSION" to exclude the sounder
- Internal selector to select alarm restore (automatic - manual )
- Internal selector to activate the timer of automatic switch off of the alarm
- Trimmer to select the time of delay of automatic switch off (from 25" to 120")
- Fuses of protection supplied and battery
- Output with cable holder
- Alarm sounder 90 dB 12Vcc
- Internal sealed battery 12Vcc 1,2Ah
- Alarm output in free contact terminal board 250V~ 10A
- Flashing red lamp alarm 3W 12Vcc (only in model SLA1)
- Box in thermoplastic material - Protection IP55
- Dimensions 24x15x32cms(WxDxH)
- PTS is an approved MWR. Dealer